



Multifunctional Display Module MOD 20

Display with programmable inputs and outputs for Absolut-Encoder with SSI interface and Incremental Encoder

MOD 20 - a programmable multifunctional display module alternatively for one absolute single- or multi-turn encoder with SSI or parallel interface and a resolution up to 30 bit or one incremental encoder. Display parameters are fully programmable. MOD 20 has the usual standard function of a display module, but additional 9 control outputs, which can be programmed separately by 24 cam switches as comparator, cam switch or pulse switch. Easy programming by four front-panel keys or by PC with RS232 interface.

SSI-Interface

For operation of one absolute single- or multiturn- encoders with resolution up to 30 bit with serial SSI-Interface.

Incremental-Input

For operation of one incremental encoder with 3 or 6 output channels, RS422 line driver or push-pull outputs. Optically insulated with optocoupler.

Display-Scaling

Scale factor, adjustment values and counting direction are free programmable.

Programmable Control-Inputs

6 optically insulated control-inputs are programmable for various functions, e.g. storing of display data or enable of counter.

Programmable Control-Outputs

9 optically insulated control-outputs, which can be programmed separately by 24 cam switches as a comparator, cam switch or pulse switch. The cycle time is only 250 μ s.

Analogue-Output

1 optically insulated programmable analogue-output, which can be used as voltage or current output. High precision D/A-converter with 16 bit resolution.

Parallel-Interface

Optically insulated input for operation of one absolute encoder with parallel output. Optically insulated output for data output of position data or velocity data in binary, gray or BCD code.

Serial Interfaces

- RS232C One display module can be connected to a PC for programming and reading data.
- RS422/485 Up to 31 display modules can be connected to a PC.
- CANBUS Up to 32 display modules can be connected with CANBUS.

Type explanation

MOD 20

MOD 20-	1	2	3	4
Parallel interface			X	X
Analogue output		X		X
Serial interface	X	X	X	X
Programmable control inputs	X	X	X	X
Programmable control outputs	X	X	X	X
Display scaling	X	X	X	X
Incremental input	X	X	X	X
SSI interface	X	X	X	X

Technical data

Technical Data

Supply voltage	+10 ... 35 VDC
Power consumption	< 150 mA (ohne Last / without load)
Cycle time	250 µs
Display range	-9999999 ... 99999999
Display	rote 7-Segment-LED-Anzeige 8-stellig mit 14 mm Ziffernhöhe <i>8-digit 7-segment red LED display, 14 mm high</i>
Data memory	EEPROM
Operating temperature	0 ... +50°C
Connections	Klemmleiste / <i>Terminal block</i> max. 1,5 mm ² Sub-D-Stecker / <i>Sub-D connector</i>
Weight	< 0,7 kg
Protection class	Frontplatte / <i>front</i> : IP 50 mit Schutzgehäuse / <i>with protective cover</i> : IP 54 Rückseite / <i>rear</i> : IP 20

Incremental input

Circuit	Optokoppler
Input level 5 VDC	High +2,8 ... +5 VDC Low 0 ... +0,8 VDC
Input level 24 VDC	High +10 ... 35 VDC Low 0 ... +5 VDC
Input resistance	3 kOhm, $U_{in} = 24 V$ 350 Ohm, $U_{in} = 5 V$
Input frequency	max. 150 kHz
Pulse width signal M	min. 2 µs

SSI interface

Clock frequency	125 kHz, 139 kHz
Clock output	RS422
Clock input	Optokoppler RS485

Control inputs

Circuit	Optokoppler
Input level Low	0 ... +5 VDC
Input level High	+10 ... 35 VDC
Input resistance	1,8 kOhm, $U_{in} = 24 V$

Control outputs

Circuit	Optokoppler mit NFET-Treiber
Supply voltage	max. +35 VDC
Output voltage	min. $V_{cc} - 2 V$, $I_{out} = 50 mA$
Output current	max. 500 mA, kurzschlussfest / <i>short-circuit proof</i>

Analogue Voltage-Output

oltage range	-10 ... +10 VDC
Resolution	305 µV = 16 Bit
Temperature stability	max. 20 ppm / °C
Output current	max. 12 mA, kurzschlußfest / <i>short-circuit proof</i>

INDUcoder® · INDUcoder Messtechnik GmbH, Kaiserstraße 316, 47178 Duisburg, Deutschland
Tel: (0203) 57047-0, Fax: (0203) 57047-20, E-Mail: info@inducoder.de, Internet:
www.inducoder.de