EZEncoders



## **Encoder** Cables and Accessories

## **MS Connector Cables**

Part #	Interface	Price			
	5 Pin M12 Connector				
CBL-5PIN-M12-002	5 pin, M12 Conn. with 2ft shielded cable	\$40			
CBL-5PIN-M12-005	5 pin, M12 Conn. with 5ft shielded cable \$				
CBL-5PIN-M12-020	5 pin, M12 Conn. with 20ft shielded cable				
CBL-5PIN-M12-050	5 pin, M12 Conn. with 50ft shielded cable \$				
CBL-5PIN-M12-100	5 pin, M12 Conn. with 100ft shielded cable \$				

7 PIN M16				
CBL-7PIN-M16-002	7 pin, M16 Conn. with 2ft shielded cable	\$50		
CBL-7PIN-M16-005	7 pin, M16 Conn. with 5ft shielded cable \$			
CBL-7PIN-M16-020	IN-M16-020 7 pin, M16 Conn. with 20ft shielded cable			
CBL-7PIN-M16-050	7 pin, M16 Conn. with 50ft shielded cable			
CBL-7PIN-M16-100	7 pin, M16 Conn. with 100ft shielded cable	\$335		

8 PIN M12				
CBL-8PIN-M12-002	8 pin, M12 Conn. with 2ft shielded cable	\$60		
CBL-8PIN-M12-005	8 pin, M12 Conn. with 5ft shielded cable \$			
CBL-8PIN-M12-020	8 pin, M12 Conn. with 20ft shielded cable			
CBL-8PIN-M12-050	8 pin, M12 Conn. with 50ft shielded cable \$			
CBL-8PIN-M12-100	8 pin, M12 Conn. with 100ft shielded cable			

10 PIN M12				
CBL-10PIN-M12-002	10 pin, M10 Conn. with 2ft shielded cable	\$65		
CBL-10PIN-M12-005	10 pin, M10 Conn. with 5ft shielded cable			
CBL-10PIN-M12-020	10 pin, M10 Conn. with 20ft shielded cable			
CBL-10PIN-M12-050	10 pin, M10 Conn. with 50ft shielded cable \$			
CBL-10PIN-M12-100	10 pin, M10 Conn. with 100ft shielded cable	\$445		

## MS-Connector Cable CBL-5PIN-M12-005 A B C D

- A: Encoder Cable
- B: 5PIN, 7PIN, 8PIN, 10PIN, 19PIN
- C: MS Connector: M12 (5-Pin, 8-Pin,or 10-Pin), M16 (7-Pin)
- D: 002 2 Ft
  - 005 5 Ft
  - 020 20 Ft
  - 050 50 Ft
  - 100 100 Ft 100 – 100 Ft8

M12 5-pin Pin-out					
Connector	Pin	config	Wire Color		
	A	A	Red		
D E	В	В	Yellow		
( ● A● )	(● ) C	A● ) C	Ground	White/Black	
C • • B	D	A	Red		
	E	Z	Green		

M16 7-pin Pin-out					
	Pin	A B Z	Wire Color	ABZ	Wire Color
Connector		config		config	Wire Color
	А	A	White	A	Red
	В	В	Blue	В	Yellow
$ \begin{array}{c} F \bullet_{\mathbf{G}} \bullet_{\mathbf{B}} \\ \bullet \bullet \bullet \bullet \\ E \bullet_{\mathbf{D}} \bullet \mathbf{C} \end{array} $	С	Z	Yellow	A-	Red/Black
	D	Power	Red	Power	White
	E	NC	-	B-	Yellow/Black
	F	GND	Black/Green	GND	White/Black
	G	ground case		-Ground case	-

M12 8-pin Pin-out						
Connector	Pin	A B Z	Wire Color		ABZ	Wire Color
Connector		config		config		
	А	A	Red	А	Red	
	В	Power	White	Power	Yellow	
$ \begin{bmatrix} \bullet & A \\ \bullet & \bullet \\ \bullet & \bullet \\ F & \bullet \\ \bullet & \bullet \\ \end{bmatrix} $	С	-	-	A-	Red/Black	
	D	В	Yellow	В	Yellow	
	E	-	-	B-	Yellow/Black	
	F	Z	Green	Z	White/Black	
	G	ground	White/Black	ground	Green	
	Н	-	-	Z-	Green/Black	

M12 10-pin Pin-out					
Connector	Dia	A B Z	Wire Color		
	Pin	config			
	A	A	Red		
	В	В	Yellow		
	С	Z	Green		
B A	D	Power	White		
	E	NC	-		
H K JG	F	GND	White/Black		
	G	ground case	-		
	Н	A-	Red/Black		
	I	B-	Yellow/Black		
	J	Z-	Green/Black		



